

## Tabel valori grafic descarcare acumulator Li-ion 850 mAh (BL-4C)

---

Conditii test: sarcina rezistiva de 65 ohm, curentul de descarcare  $I_d = 54,4$  mA

|                |      |      |      |      |      |      |      |      |      |      |
|----------------|------|------|------|------|------|------|------|------|------|------|
| Timp (min)     | 0    | 30   | 60   | 90   | 120  | 150  | 180  | 215  | 240  | 270  |
| Descarcare [%] | 0%   | 3%   | 7%   | 10%  | 14%  | 17%  | 20%  | 24%  | 27%  | 31%  |
| Ub [V]         | 4,04 | 4,00 | 3,96 | 3,93 | 3,90 | 3,88 | 3,85 | 3,82 | 3,80 | 3,78 |

|                |      |      |      |      |      |      |      |      |      |      |
|----------------|------|------|------|------|------|------|------|------|------|------|
| Timp (min)     | 300  | 330  | 360  | 390  | 420  | 450  | 480  | 510  | 540  | 570  |
| Descarcare [%] | 34%  | 38%  | 41%  | 44%  | 48%  | 51%  | 55%  | 58%  | 61%  | 65%  |
| Ub [V]         | 3,76 | 3,74 | 3,73 | 3,72 | 3,71 | 3,70 | 3,69 | 3,68 | 3,66 | 3,64 |

|                |      |      |      |      |      |      |      |      |      |
|----------------|------|------|------|------|------|------|------|------|------|
| Timp (min)     | 600  | 630  | 660  | 690  | 720  | 735  | 750  | 765  | 780  |
| Descarcare [%] | 68%  | 72%  | 75%  | 78%  | 82%  | 84%  | 85%  | 87%  | 89%  |
| Ub [V]         | 3,61 | 3,58 | 3,54 | 3,49 | 3,44 | 3,40 | 3,35 | 3,30 | 3,20 |

